

Wifi on board

Thank you for buying the Long range Wifi and 3G system. For the set up of the units we recommend that you use the Chrome Browser from Google, this is available for Mac, PC, Android and iOS devices, we have found that some errors occur when using the other browsers, however once you have set up the system, you can use any Browser to connect to the Internet.


First, connect the units together, for a 'Kitchen table' test setup, connect the Antenna directly to the Wifi router. Then connect the long ethernet cable to the bottom of the Wifi router and to the ethernet cable block on the side marked 'PoE' (Power over Ethernet) this provides the power to the White Wifi booster.

Connect the power Supply to the PoE block and the the shorter ethernet cable to the LAN port and the other end into the the port on the 3G router. Power up the 3G router, there should now be green lights on the 3G router and blue and orange lights on the Wifi booste.

Configuration for Long Range Wifi


This requires setting up both units, some items of the configuration will be retained but some will have to be entered everytime you connect to a Wifi Hotspot at a Marina etc.

Open your Chrome browser and select the 3G router's Wifi network which will besomething like 'HUAWEI-E5730-EDAB' and enter the wifi code which is printed inside the back of the unit and will be something like 'h9mhr89r', then in the address bar type '192.168.8.1' and press enter and you should the following screen.




Wifi on board

Click on Connection settings and you will get a box to enter the username and password these are both 'admin'




Click on the Ether and select settings 'Static route', and configure IP Address as 192.168.2.100, Subnet Mask, 255.255.255.0, The Default gateway and DNS Servers as 192.168.2.1. and click "Apply"




The unit will connect via the ethernet cable to the Wifi booster and the globe in the top right corner of the screen will go blue along with the network icon this will be lit on the front of the box as well.

Wifi on board

Then open an new 'Tab' on the browers and type '192.168.2.1'in the address bar and you will get the management screen from the Wifi booster, again username is 'admin' and password is 'admin' and click 'login'




You will now get the following screen,




Click 'Easy Setup and select 'Client Router Mode' and click on 'Next'

Long Range Wifi and 3G Chrome quick reference guide

Wifi on board




On the next screen click 'Site Survey'




Long Range Wifi and 3G Chrome quick reference guide

Wifi on board

Select the AP your require, the system will connect to most Wifi access points with a signal greater than -80dB ie -79dB to 0dB. Weaker signals may connect down to -92dB providing the Hotspot is set up with external antenna etc. Select the Wifi you want in this case BT with FON and click 'Select'




Now select 'Next', if you have selected a known Wifi with and access code you will be asked to enter this as the 'Passkey' So if you have been to a Bar and have the code this is where you enter it. Set the power level to 24-27 if requested.




Wifi on board

Select Next,




Leave the DNS settings blank and select 'Next'. The configuration is done and you will get a reset message,




Wifi on board

Open another tab and you should be connected in this case to BT Openzone, enter your account details and you are connected, all other devices will not need to login to BT or the Wifi provider.




Wifi on board

To Connect to 3G, first power off the unit and insert your SIM card into the unit switch on. Logon as before and go to the 3G routers Management page on 192.168.8.1 and select the dial settings, and profile management and enter the SIM Apn settings, the majority of UK Sims are sett but some like GiffGaff and Tesco mobile will need to be set. Details at the end of the document. For other SIM look at http://wiki.apnchanger.org/Main_Page most SIM settings can be found there.




Click Apply and then if you are connected to the Wifi booster go to ethernet settings and select LAN only and the unit will connect to the 3G provider.



The the globe will go blue and the network icon will be replaced with the 3G signal strenght bars on the web page and on the front of the unit.You are now connected to the internet.

Wifi on board

If the Wifi booster is unplugged the unit will automatically connect via the 3G network.



Wifi on board

List of APN configurations for the UK.

"3" UK (Any SIM)

APN: 3internet

Username: [leave blank]

Password: [leave blank]

abroadband (Any SIM)

APN: mdata.com

Username: mdata@mdata.com

Password: ppp

Airtel-Vodafone Channel Islands (Any SIM)

APN: airtel-ci-gprs.com

Username: [leave blank]

Password: [leave blank]

ASDA Mobile UK (Any SIM)

APN: asdamobiles.co.uk

Username: web

Password: web

Brightroam (UK originating SIM)

APN: mobile.o2.co.uk

Username: username

Password: password

BT Mobile UK (Any SIM)

APN: btmobile2.bt.com

Username: bt

Password: bt

co-operative mobile (Any SIM)

APN: tslpaymnet

Username: [leave blank]

Password: [leave blank]

Delight Mobile UK (Any SIM)

APN: internet

Username: [leave blank]

Password: [leave blank]

EE/Everything Everywhere UK (Any SIM)

APN: everywhere

Username: eesecure

Password: secure

Fogg Mobile (Any SIM)

APN: internet.foggmobil.com

Username: [leave blank]

Password: [leave blank]

Wifi on board

giffgaff UK (Any SIM)

APN: giffgaff.com

Username: giffgaff

Password: password

globalgig (UK sim)

APN: mbb.voiammo.net

Username: [leave blank]

Password: [leave blank]

JT (Jersey Telecom) (Any SIM)

APN: pepper

Username: [leave blank]

Password: [leave blank]

Lebara UK (Any SIM)

APN: uk.lebara.mobi

Username: wap

Password: wap

Lyca Mobile UK (Any SIM)

APN: data.lycamobile.co.uk

Username: lmuk

Password: plus

Manx Telecom - Isle of Man (Any SIM)

APN: 3gpronto

Username: [leave blank]

Password: [leave blank]

Maxroam (Any SIM)

APN: maxroam.com

Username: maxroam

Password: maxroam

MobiData (Any SIM)

APN: mbb.voiammo.net

Username: [leave blank]

Password: [leave blank]

Now Mobile (Any SIM)

APN: nowmobilenet

Username: [leave blank]

Password: [leave blank]

o2 UK (Contract SIM)

APN: mobile.o2.co.uk

Username: web

Password: web

Wifi on board

o2 UK (Pay As You Go SIM from a DONGLE)

APN: m-bb.o2.co.uk

Username: web

Password: web

o2 UK (Pay As You Go SIM from a prepaid PHONE)

APN: payandgo.o2.co.uk

Username: web

Password: web

Orange UK (Any SIM)

APN: orangeinternet

Username: [leave blank]

Password: [leave blank]

Ovivo Mobile (Any SIM)

APN: ovivomobile.com

Username: [leave blank]

Password: [leave blank]

Samba Mobile (Any SIM)

APN: 3internet

Username: [leave blank]

Password: [leave blank]

Sure Mobile Guernsey (Any SIM)

APN: internet

Username: [leave blank]

Password: [leave blank]

Sure Mobile Isle of Man (Any SIM)

APN: internet

Username: [leave blank]

Password: [leave blank]

T-mobile UK (Any SIM)

APN: general.t-mobile.uk

Username: [leave blank]

Password: [leave blank]

Talkmobile UK (Contract SIM)

APN: talkmobile.co.uk

Username: wap or [leave blank]

Password: wap or [leave blank]

Talkmobile UK (Pay As You Go SIM)

APN: payg.talkmobile.co.uk

Username: wap or [leave blank]

Password: wap or [leave blank]

Wifi on board

TalkTalk UK (Any SIM)

APN: mobile.talktalk.co.uk

Username: wap

Password: wap

Tesco Mobile UK (Prepay SIM)

APN: prepay.tesco-mobile.co.uk

Username: tescowap

Password: password

Three UK (Any SIM)

APN: 3internet

Username: [leave blank]

Password: [leave blank]

Truphone (Any SIM, Any Tru Country)

APN: truphone.com

Username: [leave blank]

Password: [leave blank]

Vectone UK (Any SIM)

APN: webuk.mundio.com

Username: [leave blank]

Password: [leave blank]

Virgin UK (Any SIM)

APN: goto.virginmobile.co.uk

Username: user

Password: [leave blank]

Vodafone UK (Contract SIM from any phone or dongle or iPad)

APN: internet

Username: web

Password: web

Vodafone UK (PayAsYouGo SIM from a dongle:"2GB valid 30 days")

APN: ppbundle.internet

some 2013 sims have been found to use APN: smart

Username: web

Password: web

Vodafone UK (PayAsYouGo SIM from a MiFi:"2GB valid 30 days")

APN: ppbundle.internet **or** pp.internet

some 2013 sims have been found to use APN: smart

Username: web

Password: web

Vodafone UK (PayAsYouGo SIM from a dongle: "1GB valid 30 days")

APN: pp.internet

Wifi on board

Username: web

Password: web

Vodafone UK (PayAsYouGo SIM from a dongle: "1GB valid 90 days")

APN: pp.internet

Username: web

Password: web

Vodafone UK (PayAsYouGo SIM from a dongle: "250mb valid 30 days")

APN: smart

some 2014 sims have been found to use APN: pp.internet

Username: web

Password: web

Vodafone UK (PayAsYouGo SIM from a dongle: "1GB no expiry")

APN: pp.bundle *or* pp.internet

Username: web

Password: web

Vodafone UK (PayAsYouGo SIM from an iPad: "250mb valid 30 days")

APN: smart

Username: web

Password: web

Vodafone UK (PayAsYouGo SIM from a tablet: "250mb valid 30 days")

APN: smart

some 2014 sims have been found to use APN: pp.internet

Username: web

Password: web

Vodafone UK (PayAsYouGo SIM from any prepay phone)

APN: pp.vodafone.co.uk

Username: web

Password: web