Thank you for buying the LTE 4G and Long range Wifi system. For the set up of the units we recommend that you use the Chrome Browser from Google, this is available for Mac, PC, Android and iOS devices, we have found that some errors occur when using the other browsers, however once you have set up the system, you can use any Browser to connect to the Internet.

Insert your data SIM card into the SIM slot and plug the LTE 4G router in and power up, after about 30seconds the WIFI name WR-LTE router will appear in your Wifi networks select it and enter the WiFi Password: 666666666 and your device will connect to the LTE 4G router

Open a Chrome browser on your Computer and type the following address in the the Chrome address bar. 192.168.0.1 and hit the return key as below,

♥ ♥ ♠ 10 192/368.01 - 0.001 © 102/36.01 - 0.001 © 0.01 0.001 0.	New Tab	×					
192356.31 - 103 (32) (SR) antr 1923156.32 - 103 (32) (SR) antr 1923156.31 - 103 (32) (SR) antr 1923156.32 - 103 (32) (SR) antr 1923156.31 - 103 (32) (SR) antr 1923156.32 - 103 (32) (SR) antr 1923156.31 - 103 (32) (SR) antr 1923156.31 - 103 (32) (SR) antr 1923156.31 - 103 (32) (SR) antr 1923157 - 103 (SR) (SR) (SR) (SR) (SR) (SR) (SR) (SR)	→ C fi [] 192.168.0.1						9
192.168.2.1 - 11.N.3C.USB.Router 192.17.17.17.17.17.17.17.17.17.17.17.17.17.	192.168.0.1 -	Oops! Google Chrome could	I not connect to 192.168	1.0.1			
192.188.169.1/interret/ven.asp - Unsufforted Unsuffered Unsuffere	192.168.2.1 -	1N_3G_USB_Router					
9, 19- Coogle Sarch	192.168.169.1	(internet/wan.asp - Unauth	orized:Unauthorized				
پ ن جن از م	Q 19 - Google Se	irch					
					1		
		4				Ŷ	
	[Ŷ	
	[, , ,	Ŷ	
						Ŷ	
			www.outilgoes.com			Ų.	
			www.outilgoes.com			Ų.	

You will now get the logon from the LTE 4G router in a pop up box both the username and password is 'admin' enter these into and select 'Login'

🗯 Chrome File Edit View History Bookmarks Wi	Vindow Help 🛛 😌 🎧 🛫 🕴 🕙 📿 🐠 🌐 63% 🗊 Thu 15:41 David Walker 🝳	/=/
		H _M
← → 🗙 🖍 🗋 192.168.0.1	☆ 9	=
🗰 Apps 🔝 NICEIC Building Reg: 🗯 Apple 🔛 Yahool 🙁 loose cov	svers derbysi ! Google Maps 🔹 YouTube 📄 News 🐨 Wikipedia 📄 Popular 🗋 Fully Pumped System 👘 Other Bookm	arks
	Authentication Required × The server http://19.2168.0.1:80 requires a username and password. The server says: Wireless Access Point. User Name: Password: Cancel Log In	
	L 🛛 🎅 📑 🖏 👬 🐼 👬 🐇 두 🌮 Lui 🔂 🖄 😒 💆 🖄 🚱 😒 💬 🖿 🗎	1

You will now get the main screen of the LTE 4G router and select the Wizard tab.

NICEIC Build	ing Regi 🧯 Apple 🔛 Ya	thoo! <u>8</u> loose cover:	derbys) 🔣	Google Maps	YouTube	News W Wikip	edia 🚞 Popular 🗋	Fully Pumped System	Cther Bo
	101010101000 x0000 0011501900		Wirel	ess 11	N Rou	iter			
	Wizard Status	Operation Mode	Wireless	Network	Firewall	Management		Help	
	Status						Er	iglish 🛟	
	WAN Configuration								
		WAN Status 4G	LTE) - Dialing						
		Connect Type 4G	LTE) Connectio	n					
		WAN IP							
		Subnet Mask							
		Deafult Gateway							
		DNS 0.0	0.0					_	
	Modem Info	MAG							
		Manufacturer Sier	ra Wireless, Ind	corporated					
		Model Mod	el: MC7710	(Vendor=1199	Product=68	a3)			
		Network LTE							
		USIM Status N/A							
		Signal Strength							

Select the wizard and 3/4G Mode

00 (ind mander S
Wireless R	outer × https://www.	google.co.uk ×			
	ding Reg.	loose covers derbys	YouTube News W Wikipedia	Popular C Fully Pumped System	Other Bookman
	HOLOIOILAN COLOIO				
	ont ISOF	Wireless 11	N Router		
	.atolu.ato	Witeress II			
	Wizard Status Op	eration Mode Wireless Network	Firewall Management	@ Help	
	Wizard			English 🛟	
	Operation Mode	In this words, the device is successed by		The NAT is see blad and DOs	
	Gateway Mode	in LAN ports share the same IP to ISP	through WAN port. The connection type ca	n be setup in WAN page by	
	3G/4G Mode	In this mode, the device is supposed t	P. to connect to internet via 3G/4G network。Ti	he NAT is enabled and PCs in	
	© 38/48 mode	LAN ports share the same IP to ISP th	nrough WAN port.		
				Cancel Back Next	

On the next screen enter the Mobile network settings I suggest that you set the mode to Auto and the Then set the APN settings in this case it is for EE in the UK and the APN is called 'everywhere' the username is 'eesecure' and the password is 'secure'.

attached are the main APN setting for most UK networks

		densys 💽 doogre	maps a rourabe [KODULAR EULOZ KURDARI	Sustan Other
	TANK AND				\sim	
		Wireles	s 11N Rou	ter 😹		
	Carlin Constitute Made	Window No.	turate Element		@	
	operation mode	Wireless Ne	work Firewall	management	(7) Help	
vviza	•				English	-
	tting					
	WAN Setting	Moblie	¢)			-
Moblie						
	Network Model	(4G \$)				-
	APN	everywhere				
	User Name					
	User Password					-
S Adv	vanced Settings					
					Cancel Back Nex	ct .

Leave the LAN IP settings and click Next,

📫 Chrome File E	dit View History Bookmarks Window Help 🛛 🚱 🖓 😌 🍀 🎧 🦿 🕯 🍀 🖓 奈 🚸 🎟 53% 🖅 Thu 16:54 David Walker ୣ 🖓	
OOO Wireless Rout	er × 18 https://www.google.co.uk ×	
← → C fi 🗋 192.	168.0.1/wizard.asp @ 😭 🔍	
🔛 Apps 🔝 NICEIC Building	Reg 🧉 Apple 🙀 Yahool 💈 loose covers derbysi 🔮 Google Maps 💶 YouTube 📄 News 🖤 Wikipedia 📄 Popular 🕒 Fully Pumped System 👘 Other Bookmarks	
	Wireless 11N Router	
	Wizard Status Operation Mode Wireless Network Firewall Management @ Help	
	Wizard English	
	IP Address 192 168 0 1	
	Subnet Mask [255], [255], [255], [0	
	DHCP Server Setting	
	DHCP Server Enable Disable Disable	
	DHCP Client IP 192 . 168 . 0 . 2 - 192 . 168 . 0 . 254	
	DHCP Lease Time B6400 Range: (300-864000)s	
	Cancel Back Next	
	Ĩ````````````````````````````````````	

Either leave the Wireless settings as they are or configure the Wifi name and the secuirity mode and click 'Finished' the unit will reboot,

🗯 Chrome File Ec	lit View	History B	ookmarl	ks Windo	w Help		90 (<u>କିଲ୍ଟ</u> ା ଏବ	* 0 0	•) 🔠	56% 🗺 Thu 16:58	David Walker	Q/=
OOO / Wireless Route	er ×	8 https:/	/www.goo	gle.co.uk ×									м ₂₁
← → C ㎡ 🗋 192.1	68.0.1/wiza	rd.asp										Q. 52	9 ≡
Apps 🔝 NICEIC Building	Regi 🧉 App	le 🝸 Yaho	o! <u>8</u> l	oose covers o	derbysh 🔣 G	oogle Maps	YouTube	News W	7 Wikipedia	Popular	Fully Pumped Sys	tem 📄 Other Bo	okmarks
	1010101P 00115019	atoloio			Wirel	ess 1 [.]	1N Rou	uter			¥//		
	Wizard	Status	Operat	tion Mode	Wireless	Network	Firewall	Managemer	ent		🕜 Help		
											English 🛟		
	Basic Settin	g											
			Status	Enable		0	Disable						
			SSID	Wifionboard	4G		Mode B	,G,N 🛊					
		F	tegional	FCC	\$		Channel A	uto Select	🗘 🗌 Intel	ligent optimiz	ation 12 🗘 Hours		
		Brodcas	st SSID	Enable		0	Disable						
			WMM	Enable			Disable						
		Authen	tication	Open Syst	em 🛊)							
		End	cryption	None	WEP64 O W	/EP128 🔍 T	KIP AES	TKIP/AES					
										Cancel	Back Finished		
												Google Chrome	
													8 My Day
<u> </u>	×00	0 30 0	P	- 🛃 🖗			🕆 🤣 🐿	🔊 👼 S		20' 🗞			6

The unit will reboot and connect to the 3/4G Mobile service logon and check the status of the unit,

	<u> </u>									
192.168.0.1/system	_status.asp		Pm						oogle	
Most Visited * Marca (3193 unre	ead) 👹 Gel	tting Started	Latest Head	ines 👻 📴 Bi	boking summ	ary [_] Boo	okings Overvi	nttps://www.nw	Verview - Goo	D [] EnterCompanyD)
		10/01010								
				Wirolo	000 111		tor	ALL ALL		
		and and		wirele	55 111	N KOU				
	Wizard	Status Op	peration Mode	Wireless	Network	Firewall	Management		Relp	
	Status							E	nglish ÷	
	WAN Configu	uration							_	
			WAN Status 3	G(WCDMA)- C	onnected					
			Connect Type 3	G(WCDMA) Co	nnection					
			WAN IP 1	0.5.52.56						
			Subnet Mask 2	55.255.255.255	5					
		De	afult Gateway 1	0.5.52.56						
			DNS 1	09.249.185.224	109.249.19	0.32				
			MAC A	2:D1:CA:2A:01:	:07					
	Modem Info									
			Manufacturer Si	erra Wireless, I	ncorporated					
			Model M	odel: MC7710	(Vendor=119	99 Product=	68a3)			
			Network W	CDMA						
			USIM Status U	SIM inserted						
		s	Signal Strength		58	%				
	LAN Configur	ration								

4G APN Settings

Everything Everywhere / EE 4G APN

APN : everywhere User Name : eesecure Password : secure

O2 4G APN Settings

APN : idata.o2.co.uk User Name : vertigo Password : password

APN : mobile.o2.co.uk User Name : o2web Password : password

Vodafone 4G APN Settings

APN : internet User Name : Leave Blank Password : Leave Blank

3G APN Settings

"3" UK (Any SIM)

APN: 3internet Username: [leave blank] Password: [leave blank] abroadband (Any SIM)

APN: mdata.com Username: mdata@mdata.com Password: ppp

Airtel-Vodafone Channel Islands (Any SIM)

APN: airtel-ci-gprs.com Username: [leave blank] Password: [leave blank]

ASDA Mobile UK (Any SIM)

APN: asdamobiles.co.uk Username: web Password: web Brightroam (UK originating SIM) APN: mobile.o2.co.uk

Username: username Password: password **BT Mobile UK (Any SIM)** APN: btmobile2.bt.com Username: bt Password: bt co-operative mobile (Any SIM) **APN: tslpaymnet** Username: [leave blank] Password: [leave blank] EE UK (Any SIM) **APN: everywhere** Username: eesecure Password: secure giffgaff UK (Any SIM) APN: giffgaff.com Username: giffgaff Password: password globalgig (UK sim) APN: mbb.voiamo.net Username: [leave blank] Password: [leave blank] JT (Jersey Telecom) (Any SIM) **APN:** pepper Username: [leave blank] Password: [leave blank] Lebara UK (Any SIM) APN: uk.lebara.mobi Username: wap Password: wap Lyca Mobile UK (Any SIM) APN: data.lycamobile.co.uk Username: Imuk Password: plus Manx Telecom - Isle of Man (Any SIM) **APN: 3gpronto** Username: [leave blank] Password: [leave blank] MobiData (Any SIM) APN: mbb.voiamo.net

Username: [leave blank] Password: [leave blank] Now Mobile (Any SIM) **APN:** nowmobilenet Username: [leave blank] Password: [leave blank] o2 UK (Contract SIM) APN: mobile.o2.co.uk Username: web Password: web o2 UK (Pay As You Go SIM from a DONGLE) APN: m-bb.o2.co.uk Username: web Password: web o2 UK (Pay As You Go SIM from a prepaid PHONE) APN: payandgo.o2.co.uk Username: web Password: web **Orange UK (Any SIM)** APN: orangeinternet Username: [leave blank] Password: [leave blank] **Ovivo Mobile (Any SIM)** APN: ovivomobile.com Username: [leave blank] Password: [leave blank] Samba Mobile (Any SIM) **APN: 3internet** Username: [leave blank] Password: [leave blank] Sure Mobile Guernsey (Any SIM) APN: internet Username: [leave blank] Password: [leave blank] Sure Mobile Isle of Man (Any SIM) **APN:** internet Username: [leave blank] Password: [leave blank] T-mobile UK (Any SIM) APN: general.t-mobile.uk

Wifi on board ا

Username: [leave blank] Password: [leave blank] Talkmobile UK (Contract SIM) APN: talkmobile.co.uk Username: wap or [leave blank] Password: wap or [leave blank] Talkmobile UK (Pay As You Go SIM) APN: pavg.talkmobile.co.uk Username: wap or [leave blank] Password: wap or [leave blank] TalkTalk UK (Any SIM) APN: mobile.talktalk.co.uk Username: wap Password: wap **Tesco Mobile UK (Prepay SIM)** APN: prepay.tesco-mobile.co.uk Username: tescowap Password: password Three UK (Any SIM) **APN: 3internet** Username: [leave blank] Password: [leave blank] Truphone (Any SIM, Any Tru Country) APN: truphone.com Username: [leave blank] Password: [leave blank] Virgin UK (Any SIM) APN: goto.virginmobile.co.uk Username: user Password: [leave blank] Vodafone UK (Contract SIM from any phone or dongle or iPad) APN: internet Username: web Password: web Vodafone UK (PayAsYouGo SIM from a dongle:"2GB valid 30 days") APN: ppbundle.internet some 2013 sims have been found to use APN: smart Username: web

Password: web

Vodafone UK (PayAsYouGo SIM <u>from</u> a MiFi:"2GB valid 30 days")

APN: ppbundle.internet ***or*** pp.internet

some 2013 sims have been found to use APN: smart Username: web Password: web Vodafone UK (PayAsYouGo SIM from a dongle: "1GB valid 30 days") APN: pp.internet Username: web Password: web Vodafone UK (PayAsYouGo SIM from a dongle: "1GB valid 90 days") APN: pp.internet Username: web Password: web Vodafone UK (PayAsYouGo SIM from a dongle: "250mb valid 30 days") APN: smart some 2014 sims have been found to use APN: pp.internet Username: web Password: web Vodafone UK (PayAsYouGo SIM from a dongle: "1GB no expiry") APN: pp.bundle ***or*** pp.internet Username: web Password: web Vodafone UK (PayAsYouGo SIM from an iPad: "250mb valid 30 days") APN: smart Username: web Password: web Vodafone UK (PayAsYouGo SIM from a tablet: "250mb valid 30 days") APN: smart some 2014 sims have been found to use APN: pp.internet Username: web Password: web Vodafone UK (PayAsYouGo SIM from any prepay phone) APN: pp.vodafone.co.uk Username: web Password: web